

ET-KB800 Remote Control Keyboard

ET-KB800 provides you with a more convenient, simpler, and direct remote controller. With RS-422 communication (9600 baud per second) connecting to peripherals for control Video Switching on MEGAsys' main system frame quickly and accurately, Combing with MEGAsys Matrix mainframe it remotely control all major brand surveillance cameras, monitors, circuit loop PTZ, iris, focus and zoom etc. With ET-50, ET-100, ET-200, ET-300, ET-2000 or ET remote accessory control unit, it can further increase control on preset location of circuit loops, and parts like iris, focus and zoom.



0-9 Number Control Panel

This Number Control Panel allows you to select the camera or monitor you wish to view, press camera then the number of the camera you want to view then press the enter key. Same with monitor as you press the monitor key with the number key then press enter to view the desired monitor. If you wish to view a different camera view on certain monitor just select the camera you wish to view using the \updownarrow key.

Controlling Circuit Loop and Vari-Focal lens etc.

Operator uses the keyboard to select circuit loop, Focal Lenses and monitor, then control their vertical, horizontal movement with the joystick, using iris, focus and zoom key to control the movement of the focal lenses. KB-800 provides 6 function keys, Operator can set them to ET-100, ET-200 or ET-300 Remote accessory control unit relay, activating water sprinkler, windscreen wiper, lights, fog remover or any other devices' power.

Operator PIN Protection

All Operator needs to have a personal PIN to enter the controlling system. KB-800 keyboard require an Operator password once connected to power, the system will verify the password before allowing the user to operate. (Password needs to be 4 digits number and it only works on MEGAsys.)

Patrol System Control Panel Support

KB-800 is specifically designed for security purpose and it uses hard painted plastic insulated cover, prevent dirt and water resistant, it is very practical and reliable, easy to place on control tables, or placed aside by brackets. MEGAsys supports image patrol memory setting, each time set for 24 people and all 100 procedures. It can define image patrol's time and location procedural functions by linking the process to MEGAsys' mainframe and simultaneously with the patrolling database that are beneficial for security management.

Features

- Easy to place on desktops, or add support and place on control tables.
- RS-422
- LCD Monitor (95mm x 17mm).
- Circuit Loop PTZ & joystick operation.
- Lenses control including: Iris, Focus and Zoom.
- Water Sprinkler, windscreen wiper, lights, and any devices' power
- Location preset, output control including: iris, focus, zoom, circuit loop PTZ.
- Prevent dust, water resistant plastic cover; practical, reliable and easy to clean.
- Uses standard keyboard button, easy to use.
- AC100-220V 50/60Hz power supply – Size (260(W) x 210(D) x 75(H) mm).
- (MEGA/MAX System Only) PIN can divide into 8 groups according to management and control.
- (MEGA/MAX System Only) Operator needs to enter personal PIN to enter the control system.
- Size - 260(W) x 210(D) x 75(H) mm.